

Fluorescent / LED Equivalent Chart (2x2)

Lamp	# Lamps	Designation (enter in Box 2)	LED Output	Input Watts
F17T8	2	A	2000 L	17 W
	3	B	3000 L	24 W
	4	C	4000 L	32 W
	5	D	4875 L	40 W
	6	E	5900 L	49 W

Fluorescent / LED Equivalent Chart (2x4)

Lamp	# Lamps	Designation (enter in Box 2)	LED Output	Input Watts
F32T8	2	F	4250 L	33 W
	3	G	6225 L	48 W
	4	H	8400 L	68 W
	5	J	10160 L	82 W
	6	K	12170 L	102 W

Coefficients of Utilization - Zonal Cavity Method (M607-LED 2x4)

Effective Floor Cavity Reflectance: 20%

RCC %:	80				70				50			30			10			0
RW %:	70	50	30	0	70	50	30	0	50	30	20	50	30	20	50	30	20	0
RCR: 0	1.19	1.19	1.19	1.19	1.16	1.16	1.16	1.00	1.11	1.11	1.11	1.06	1.06	1.06	1.02	1.02	1.02	1.00
1	1.10	1.05	1.01	.98	1.07	1.03	.99	.86	.99	.96	.93	.95	.92	.90	.91	.89	.88	.86
2	1.00	.92	.86	.80	.97	.90	.84	.73	.87	.82	.78	.84	.79	.76	.81	.77	.74	.72
3	.91	.81	.73	.67	.89	.80	.72	.63	.77	.71	.65	.74	.69	.64	.72	.67	.63	.61
4	.84	.72	.64	.57	.82	.71	.63	.54	.69	.62	.56	.66	.60	.55	.64	.59	.55	.53
5	.77	.65	.56	.50	.75	.64	.55	.48	.62	.54	.49	.60	.53	.48	.58	.52	.48	.46
6	.71	.58	.50	.43	.70	.58	.49	.42	.56	.48	.43	.54	.48	.43	.53	.47	.42	.40
7	.66	.53	.45	.39	.65	.52	.44	.37	.51	.43	.38	.49	.43	.38	.48	.42	.38	.36
8	.62	.49	.40	.34	.60	.48	.40	.34	.47	.39	.34	.45	.39	.34	.44	.38	.34	.32
9	.58	.45	.37	.31	.56	.44	.36	.30	.43	.36	.31	.42	.35	.31	.41	.35	.31	.29
10	.54	.41	.33	.28	.53	.41	.33	.28	.40	.33	.28	.39	.32	.28	.38	.32	.28	.26

M607-LED - Polar Candela Distribution (M607-LED 2x4)

